

### ES105-5-CO2 / ES105-5-PM

### High Integrated Out-Door Weather Station CO<sub>2</sub>, PM<sub>2.5</sub>, Illumination, Temperature, Humidity, Noise, Atmospheric Pressure Sensor

The ES105 series is an intergraded outdoor sensor unit for all types of environmental and weather monitoring sensors include illumination, temperature, humidity, noise, Atmospheric Pressure and CO<sub>2</sub> or PM<sub>2.5</sub>&10. The monitored data is output through RS-485 interface by Modbus protocol. The ES105 sensor unit accepts 10~30Vdc power input voltage and is protected by the IP65 grade Anti-U/V lightweight ABS louver radiation shield. With the optional NBloT/WiFi gateway WR222 or LoRa end node LC144, the data can be monitor on the cloud platform.




One-piece shutter box structure	Multi-sensor set	A variety of detection options	Highly sensitive easy to install	Superior performance long-term stability




### Features & Benefits

- **High Integrated Monitoring**
  - Intergraded multiple sensors
  - Central management by sharing a signal output
  - Support Industrial Modbus RTU protocol, RS485
- **Outdoor Protective Enclosure**
  - Prevent direct ultraviolet radiation to the sensors
  - Avoid rapid aging of sensors under harsh environmental conditions such as strong winds, rain, and snow
  - The sensor parts are ventilated for truly sensing the changes in external detection parameters
- **Flexible Design**
  - Customized Shutter Height
    - Single or multiple parameters both can use small shutter, small size, light weight and easy to install
  - Customized Monitoring parameters
    - Each parameter is independent and high sensitivity, users can freely integrate monitoring parameters
- **Work with IoT Cloud Platform - ThingsMasterOTA**
  - Real-time online monitoring, analysis, reporting
  - Remote cloud security and visual management






## Application



## Dimensions



(mm)

**1) Sensor Connect to PC/HMI/PLC**

**2) Sensor Connect to Private LoRa to PC/HMI/PLC**

**3) Sensor Connect to LoRaWAN Gateway**

**4) Sensor Connect to LTE NB-IoT Gateway SCB111-485-NB**

**5) Sensor Connect to WiFi + LTE Gateway WR222-WLAN+LTE**


**Optional Accessory**

Item	
<b>MDR-40-24</b>	Din-Rail Power Supply INPUT:85-264VAC, 120-370VDC, OUTPUT: 24VDC/1.7A, -20 ~ +70°C
<b>ThingsMaster OTA-5GW</b>	ThingsMaster OTA for 5 gateways, One Year License
<b>LM100</b>	LoRa Master / Modbus RTU Client (Must work with LC144) (with LoRa antennas)
<b>LC144</b>	LoRa End-Node, 8CH AIO, 1 Modbus RTU 485 2-wire, 2 x 0~10V input, 2 x 4~20mA input, 1 x 0~10V Output, Open Collect (O.C.), 1 x 4~20mA Output, 1 x PWM Output (0~5V), 1 x PWM (0~10V), Open Collect (O.C.) Type, 1 x SMA /LoRa Antenna (Must work with LM100 or LM200)
<b>LR140</b>	LoRa WAN End-Node, 4CH AI, 1 Modbus RTU 485 Host, 1 x RS485 Host, 2-wire, 1 x SMA /LoRa Antenna Connector (with LoRa antennas)
<b>WR322GR-EC-LTE-LORAWAN</b>	Industrial LoRaWAN Gateway, 2GbE+2COM, LTE 2SIM, (with LTE and LoRa antennas)(Must work with LR140)
<b>WR312GR-EC-LORAWAN</b>	Industrial LoRaWAN Gateway, 2GbE+2COM (Must work with LR140)
<b>WR222-WLAN+LTE</b>	Industrial Wireless IIoT Field Router, 2FE+1COM, SD, 802.11b/g/n WLAN, 1SIM (with WiFi, LTE Antennas)
<b>SCB111-485-NB-DC</b>	Outdoor Modbus RS485 to NB-IoT / LTE Cat M1 Gateway

Temperature & Humidity	
<b>Measuring Range</b>	Temperature: -40-120 °C (Sensor Measuring Range) Humidity: 0%RH-100%RH
<b>Accuracy</b>	Temperature: $\pm 0.5^{\circ}\text{C}$ (25°C) Humidity: $\pm 3\%$ RH (5%-95% RH, 25°C)
<b>Long term stability</b>	Temperature $\leq 0.1^{\circ}\text{C}/\text{year}$ Humidity $\leq 1\%$ RH/year
<b>Response time</b>	<15/Sec (at 1m/s wind speed)
Illumination	
<b>Measuring Range</b>	0~200000 Lux
<b>Accuracy</b>	$\pm 7\%$ (25°C)
<b>Long term stability</b>	$\leq 0.5^{\circ}\text{C}/\text{Year}$
<b>Response time</b>	0.1 Sec.
CO2 (Either CO <sub>2</sub> or PM2.5/PM10)	
<b>Measuring Range</b>	0~5000ppm
<b>Accuracy</b>	$\pm 40\text{ppm} + 3\%\text{FS}$ (25°C)
<b>Long term stability</b>	$\leq 30\text{ppm}/\text{year}$
<b>Response time</b>	<10/S (1m/s wind speed)
PM2.5/PM10 (Either CO <sub>2</sub> or PM2.5/PM10)	
<b>Measuring Range</b>	0~1000ug/m <sup>3</sup>
<b>Resolution</b>	1ug/m <sup>3</sup>
<b>Accuracy</b>	$\pm 10\%$
<b>Response time</b>	<90 Sec.
Atmospheric Pressure	
<b>Measuring Range</b>	0~120Kpa
<b>Accuracy</b>	$\pm 1.5\text{Kpa}$ (25°C)
<b>Long term stability</b>	0.1Kpa/Year
<b>Response time</b>	$\leq 1$ Sec.
Noise	
<b>Measuring Range</b>	30dB~120dB
<b>Frequency Range</b>	20Hz~12.5Hz
<b>Accuracy</b>	$\pm 0.5\text{dB}$
<b>Long term stability</b>	<2%
<b>Response time</b>	$\leq 3$ seconds

System Parameters	
<b>Power Range</b>	DC 10~30V, 0.8W Power consumption
<b>Enclosure Material</b>	Shelter Box, Plastic ABS, Anti-U/V, UL94 V0
<b>Enclosure Protection</b>	IP65 Protection Level
<b>Enclosure Dimension</b>	140mm (Diameter) x 114mm (High)
<b>Communication</b>	Modbus RTU protocol, 2-Wire RS-485 RS485 Modbus RTU Pulling & Waiting Time ≥ 200mS
<b>Op. Temperature</b>	-40 ~ 60°C, 0~100% Humidity, No Condensing

Modbus Register Information			
Parameters Function	Register Add. (HEX / DEC)	PLC Add. (Index Number)	Note
Device ID Storage Add.	07D0H / 2000	2001	R/W , System Factory Default ID: 1
Serial Baud Rate Add.	07D1H / 2001	2002	R/W , Default: 2 2(9600), 0(2400), 1(4800)
Humidity	01F4H / 500	501	R/O , Real Value = Read Value/10
Temperature	01F5H / 501	502	R/O ,Real Value = Read Value/10
Noise	01F6H / 502	503	R/O , Real Value = Read Value/10
CO2 or PM2.5	01F7H / 503	504	R/O. CO2 /PM2.5 Real Value = Read Value
PM10	01F8H / 504	505	R/O, Real Value = Read Value, (Available on ES105-PM)
Atmospheric Pressure	01F9H / 505	506	R/O, Real Value = Read Value x10
Light Intensity (High)	01FAH / 506	507	R/O, Real Value = Read Value
Light Intensity (Low)	01FBH / 508	508	R/O, Real Value = Read Value

R/W: Read & Write, R/O: Read Only

## Ordering Information

Model	Description
<b>ES105-5-PM</b>	High Integrated Environmental Sensor Shelter Box, Temperature, Humidity, PM2.5/10, Illumination, Noise, Modbus RTU protocol, 2-wire RS-485 , 10~30VDC
<b>ES105-5-CO<sub>2</sub></b>	High Integrated Environmental Sensor Shelter Box, Temperature, Humidity, CO <sub>2</sub> , Illumination, Noise, Modbus RTU protocol, 2-wire RS-485, 10~30VDC
	<b>Package List</b>
	1 x Multiple Sensor Shelter Box
	1 x QIG